

← 41569, to page only

#8

delete on all page

WO 00/28334

Patent Application ~~For~~ of

delete on all pages  
PCT/EP99/08376



All CAPS

A method and system <sup>the</sup> Device and process for generation of a partly synthesized high-quality signal for acceleration of an armature of an electric drive

Title page

by Andreas Boehringer All CAPS

Field of the invention  
Attached  
page break

### Background of the Invention

In order to design high-quality position or speed control for a rotary or linear electric drive it has been customary in the past to control the components directly generating torque or force in the innermost loop, that is, in cascade control [1;2]. The most recent developments [3;4] have shown that on the other hand it is highly advantageous not to control the torque or force generating components of the current volume indicators indirectly, but to guide the acceleration of the part propelled, that is, in cascade control. In the case of rotary drives this is the spin of the rotor, and in the case of linear drives <sup>it is</sup> the linear acceleration of the armature. Hence, use of an accelerometer is required for registration of these values. <sup>is</sup> for example, <sup>One type of</sup> an accelerometer <sup>that may</sup> which operates on the Ferraris principle <sup>be used,</sup> [3;4;5]. <sup>For one thing, however, this type of</sup> For one thing, however, this accelerometer, on the whole, is characterized by a delay in measurement, albeit a small one. <sup>For</sup> another, <sup>deficiency is that</sup> this accelerometer can never be completely rigidly connected to the place engaged by rotary thrust in the case of a rotary drive, or by linear thrust in the case of a linear drive. The result of these two facts is that loop limit cycles and/or self-excited oscillations are formed in the cascade control loop for the acceleration [4]. Unless these limit cycles and/or self-excited oscillations are prevented, use of such a cascade control loop is not successful for high-quality position or speed control. A <sup>method</sup> process for suppression of these limit cycles and/or self-excited oscillations in the cascade control loop for acceleration has been proposed for rotary drives [4]. However, this process has the disadvantage that its application is.

These types of accelerometers have certain deficiencies though.

RECEIVED  
DEC-4 2002  
TECHNOLOGY CENTER 2800


41569.

### Field of The Invention



The invention relates to a method and system for controlling rotary or linear electric drives. More particularly, the invention relates to a system and method for the generation of a partly synthesized signal of high dynamic quality to control the acceleration of an armature (rotary or linear) of an electric drive. -

RECEIVED  
DEC-4 2002  
TECHNOLOGY CENTER 2800



RECEIVED

\*2-

It is therefore an object of the invention

Thus, a need exists for a low cost cascade system and method for controlling the acceleration of an armature of an electric drive that is insensitive to fluct drive and prevents fluctuations, limit cycles & self-excited oscillations in the cascade acceleration control loop.

RECEIVED  
DEC -4 2002  
TECHNOLOGY CENTER 2800

Universal change:

$F_T(p)$  for  $FT(p)$

$F_H(p)$  "  $FH(p)$

$F_g(p)$  "  $Fg(p)$

$b_{Em}$  "  $bEm$

PCT/EP99/08376

WO 00/28334

insert attached #2-1

replace  $b_m$  for  $bm$

replace  $\frac{m}{x}$  for  $m$   
"  $\frac{x}{z}$  for  $x$   
"  $\frac{z}{z}$  for  $z$

extremely costly and in addition that it reacts with extreme sensitivity to fluctuations in the parameters of the drive.

~~It is therefore an object of the invention~~  
Summary of the Invention

Replace w/attached #2-1

A partly synthesized signal of high dynamic quality for acceleration of an armature of an electric drive can be generated by means of the device claimed for the invention as proposed here. Cascade control of acceleration can be achieved by means of this signal, to a great extent independently of the parameters of the drive, while limit cycles and/or self-excited oscillations are prevented in this cascade acceleration control loop.

insert attached #2-2

### Brief Description of the Drawings

A partly synthesized signal of high dynamic quality can be generated with a device as described in Claims 1-12.

### Detailed Description of the Preferred Embodiments


insert attached #2-3

For the purpose of generating a high-quality signal for acceleration of an electric drive, first the acceleration signal,  $bm = \alpha \cdot Fg(p)$ , (in which  $Fg(p)$  describes the measurement transfer function), is first registered (a measured), and then the torque  $m$ , or the propulsive force  $f$ , as substitute acceleration signal  $bEm = m$  or  $bEm = f$ , and, in scaling the acceleration signal  $bEm$ , all losses arising throughout propulsion being disregarded and the basis adopted being that of an absolutely rigid connection of the surface engaged by the thrust of the drive to the place at which the effect used for registration of acceleration is used. The result is scaled so that the relation  $bm = \alpha \cdot Fg(p) = bEm \cdot Fg(p)$  is satisfied. The acceleration signal  $bm = \alpha \cdot Fg(p)$ , is taken to a low-pass filter with the low-pass transfer function  $FT(p)$ ; hence the signal  $x = bm \cdot FT(p)$  is present at the output of the filter, and the substitute acceleration signal  $bEm$  is input to a high-pass filter with the high-pass transfer function  $FH(p) (= FT(0) - FT(p))$ , which satisfies the relationship  $FH(p) \cdot Fg(p) = FT(0) - FT(p)$ . Adjacent to the output of which is the signal  $y = bEm \cdot FH(p)$ . Lastly, the synthesized signal  $x + y$  is formed; it is used as a substitute signal of high



### SUMMARY OF THE INVENTION

It is therefore an object of the invention to provide a system and method for controlling the acceleration of an armature of an electric drive by generating a high quality acceleration error correction signal  $z$ , the system comprising an accelerometer for obtaining a measured armature acceleration value  $\underline{b}_m$ , which is equal to the product of a true armature acceleration  $\alpha$ , and an acceleration measurement transfer function  $F_g(p)$ , and means for obtaining a measured acceleration signal,  $\underline{b}_{Em}$ , which is generated from a measured substitute acceleration signal  $\underline{b}_E$ .  $\underline{b}_m$  and  $\underline{b}_{Em}$  are scaled such that the relationship of  $\underline{b}_m = \alpha \cdot F_g(p) = \underline{b}_{Em} \cdot F_g(p)$  is satisfied. The measured armature acceleration signal  $\underline{b}_m$  is filtered with a first filter transfer function of  $F_T(p)$ , and the measured acceleration signal  $\underline{b}_{Em}$  is filtered with a second filter transfer function of  $F_H(p)$ . The first and second filter outputs are combined to form the partly synthesized high quality acceleration error correction signal  $z = \underline{b}_m \cdot F_T(p) + \underline{b}_{Em} \cdot F_H(p)$ .



\* 2-2

The ~~new~~ features and advantages of the present invention will ~~now~~<sup>best</sup> be understood by reference to the detailed description of the preferred embodiments which follows, when read in conjunction with the following drawings, in which:

Fig. 1 illustrates a control system for a plurality of electric drive types, in accordance with an embodiment of the invention;

Fig 2 illustrates a <sup>first alternative</sup> control system ~~embodiment~~ for a plurality of electric drive types, in accordance with a first alternative embodiment of the invention;

RECEIVED  
DEC - 4 2002  
TECHNOLOGY CENTER 2800




Fig. 3 illustrates a control system  
for a plurality of electric drive types,  
in accordance with a ~~first~~<sup>third</sup> alternative  
embodiment of the invention; and  
Fig. 4 illustrates a control system  
for a plurality of electric drive types,  
in accordance with a ~~fourth~~<sup>third</sup> alternative  
embodiment of the invention. —

\*2-3

The ~~various~~ various features of the preferred embodiments will now be described with reference to the drawings, in which like parts are identified with the same reference characters. The following description of the presently contemplated best mode of practicing the invention is not to be taken in a limiting sense, but is provided merely for the purpose of describing the general principles of the invention.



dynamic quality for the instantaneous armature acceleration value in automatic control of the drive.

For this purpose, in the case of rotary current propulsion, the rotary acceleration  $\alpha$  of the rotated armature is registered metrologically by an accelerometer <sup>30</sup> [3745] connected to ~~this~~ <sup>the</sup> armature and preferably operating on the Ferraris principle, and is consequently available as measured acceleration signal  $b_m \equiv \alpha \cdot F_g(p)$ .  $F_g(p)$ , with  $F_g(0) = 1$ , here represents the so-called measurement transfer function of the accelerometer. <sup>30</sup> The torque  $m$  of the <sup>electric</sup> <sup>20</sup> drive, hereafter designated as substitute acceleration signal  $b_E = m$ , is also <sup>measured</sup> ~~registered metrologically~~ and accordingly is available as measured substitute acceleration signal  $b_E = m$ . As is to be immediately perceived, use may of course be made, without impairing the operation of the device claimed for the invention, in place of the torque  $m$  of the drive, ~~also directly~~ of the torque-forming transverse-current components  $i_q$  of the current volume indicator of the rotary current fed winding of the drive <sup>20</sup> as substitute acceleration signal  $b_E = i_q$ . <sup>4</sup> In what <sup>control engineering</sup> follows, as is customary in <sup>metrology</sup>, it is assumed that <sup>with present</sup> ~~on the~~ <sup>both</sup> ~~one hand~~ the measured acceleration signal  $b_m$ , and ~~on the other~~ <sup>the</sup> measured substitute acceleration signal  $b_E$ , all losses occurring in the drive in question <sup>are</sup> ~~being~~ disregarded, and a mechanically absolutely rigid connection of the surface of the armature rotated engaged by the torque to the position of the rotated part of the rotary acceleration meter at which the effect used for registration of acceleration is generated being taken as a basis, is each scaled so that the relation  $b_m = \alpha \cdot F_g(p) = b_E \cdot F_g(p)$  is satisfied. The measured acceleration signal  $b_m$  is delivered to the input of a low-pass filter with the low-pass transfer function  $FT(p)$ ,  $FT(0)$  preferably equaling 1. Hence the signal  $x = b_m \cdot FT(p)$  can be received at the output of the low-pass

where  
with

filter. The measured substitute acceleration signal  $bEm$  is delivered to the input of a high-pass filter with high-pass transfer function  $FH(p) = FT(0) - FT(p) \cdot Fg(p)$ . Consequently, the signal  $y = bEm \cdot [FT(0) - FT(p) \cdot Fg(p)]$  may be received at this high-pass filter. A signal  $z = bm \cdot FT(p) + bEm \cdot [FT(0) - FT(p) \cdot Fg(p)]$  is now formed in accordance with the relation  $z = x + y$ . This synthesized signal is subsequently used as a very high-quality dynamic substitute as the undelayed instantaneous value of the rotary acceleration  $\alpha$  of the rotated armature in automatic control of the drive in question.

In the case of a traveling-wave drive, the linear acceleration  $\alpha$  of an armature in linear movement is ~~metrologically registered~~<sup>measured</sup> by means of an accelerometer mechanically connected to this armature, one preferably operated on the Ferraris principle transposed to linear movement, and is accordingly available as measured acceleration signal  $bm = \alpha \cdot Fg(p)$ . In this instance  $Fg(p)$ , with  $Fg(0) = 1$ , represents the so-called measurement transfer function of the accelerometer. The linear force  $f$  of the drive, to be designated in what follows as substitute acceleration signal  $bE = f$ , is also ~~registered~~<sup>measured</sup> ~~metrologically~~ and is accordingly available as measured substitute acceleration signal  $bEm$ . As is to be immediately perceived, without impairing the operation of the device claimed for the invention, the transverse-current component  $iq$  immediately forming the linear force of the current volume indicator of the multiphase current-fed winding of the drive may be used as substitute acceleration signal  $bE = iq$ . It is assumed in what follows, as is customary in control engineering, that both the measured acceleration signal  $bm$  and the substitute acceleration signal  $bEm$ , all losses occurring in the drive in question ~~being~~<sup>are</sup> disregarded and a mechanically absolutely rigid

connection of the surface of the armature rotated engaged by the torque to the position of the rotated part of the rotary acceleration meter at which the effect used for registration of acceleration is generated being taken as a basis, is each scaled so that the relation  $b_m = \alpha \cdot F_g(p) = b_{Em} \cdot F_g(p)$  is satisfied.

⊗ The measured acceleration signal  $b_m$  is delivered to the input of a low-pass filter with the low-pass transfer function  $FT(p)$ , <sup>with</sup> where  $FT(0)$  preferably equaling 1. Hence the signal  $x = b_m \cdot FT(p)$  can be received at the output of the low-pass filter. The measured substitute acceleration signal  $b_{Em}$  is delivered to the input of a high-pass filter with high-pass transfer function  $FH(p) = FT(0) - FT(p) \cdot F_g(p)$ . Consequently, the signal  $y = b_{Em} [FT(0) - FT(p) \cdot F_g(p)]$  may be received at the output of this high-pass filter. A signal  $z = b_m \cdot FT(p) + b_{Em} \cdot [FT(0) - FT(p) \cdot F_g(p)]$  is now formed in accordance with the relation  $z = x + y$ . This synthesized signal is subsequently used as a very high-quality dynamic substitute for the undelayed instantaneous value of rotary acceleration  $\alpha$  of the rotated armature in automatic control of the drive in question.

In the case of direct-current propulsion the rotary acceleration  $\alpha$  of the rotated armature is <sup>measured</sup> ~~registered~~ ~~metrologically~~ by an accelerometer ~~134,5~~ connected to this armature and preferably operating on the Ferraris principle, and is consequently available as measured acceleration signal  $b_m = \alpha \cdot$

$F_g(p)$ .  $F_g(p)$ , with  $F_g(0) = 1$ , here represents the so-called measurement transfer function of the accelerometer. The torque  $m$  of the drive, hereafter designated as substitute acceleration signal  $b_E = m$ , is also <sup>measured</sup> ~~registered~~ ~~metrologically~~ and accordingly is available as measured substitute acceleration signal  $b_{Em}$ . As is to be perceived immediately, use may of course be made, <sup>directly</sup> without impairing the operation of the device claimed for the

invention, in place of the torque  $m$  of the drive, ~~also directly~~ of the armature current  $i_a$  of the direct-current fed winding of the drive as substitute acceleration signal  $b_E = i_a$ . <sup>At</sup> In what follows, as is customary in <sup>control engineering</sup> metrology, it is assumed that ~~on the one hand~~ <sup>both</sup> the measured acceleration signal  $b_m$  and ~~on the other~~ the ~~measured~~ substitute acceleration signal  $b_{Em}$ , all losses occurring in the drive in question <sup>are</sup> being disregarded and a mechanically absolutely rigid connection of the surface of the armature rotated engaged by the torque to the position of the rotated part of the rotary acceleration meter at which the effect used for registration of acceleration is generated being taken as a basis, is each scaled so that the relation  $b_m = \alpha \cdot F_g(p) = b_{Em} \cdot F_g(p)$  is satisfied. <sup>At</sup> The measured acceleration signal  $b_m$  is delivered to the input of a low-pass filter with the low-pass transfer function  $FT(p)$ , <sup>with</sup>  $FT(0)$  preferably equaling 1. Hence the signal  $x = b_m \cdot FT(p)$  can be received at the output of the low-pass filter. The measured substitute acceleration signal  $b_{Em}$  is delivered to the input of a high-pass filter with high-pass transfer function  $FH(p) = FT(0) - FT(p) \cdot F_g(p)$ . Consequently, the signal  $y = b_{Em} \cdot [FT(0) - FT(p) \cdot F_g(p)]$  may be received at <sup>the output of</sup> this high-pass filter. A signal  $z = b_m \cdot FT(p) + b_{Em} \cdot [FT(0) - FT(p) \cdot F_g(p)]$  is now formed in accordance with the relation  $z = x + y$ . This synthesized signal is subsequently used as a very high-quality dynamic substitute as the undelayed instantaneous value of the rotary acceleration  $\alpha$  of the rotated armature in automatic control of the drive in question.

The device and the process for obtaining a partly synthesized signal of high dynamic value for acceleration of the armature of a machine is explained in detail in what follows on the basis of an example of a separately excited direct-current machine and with reference to the drawings in Figures 1 to 4.

It is advantageous <sup>in the</sup> ~~for~~ <sup>a</sup> design of high-quality position or speed control ~~for~~ <sup>to</sup> a separately excited direct-current machine to control rotary acceleration of the armature rather than the armature current in the innermost loop. For this purpose, the rotary acceleration  $\alpha$  of the rotor is ~~registered~~ <sup>measured</sup> by an accelerometer, preferably one operating on the Ferraris principle, and is accordingly available as measured rotary acceleration  $b_m = \alpha \cdot F_g(p)$ . Block 1 (see Figures 1, 2, 3, and 4) with transfer function  $F_g(p)$ , with  $F_g(0) = 1$ , describes the so-called measurement frequency response of the accelerometer. <sup>30</sup> The torque  $m$  of the drive <sup>20</sup>, which in what follows is designated as substitute acceleration signal  $b_E = m$ , is also ~~registered~~ <sup>measured</sup> ~~metrologically~~ and accordingly is available as measured substitute acceleration signal  $b_{Em}$ . Armature current  $I_a$  of the direct-current-fed armature winding of the drive may, of course, also be used as substitute acceleration signal  $b_E = i_a$  in place of the moment  $m$  of the drive. <sup>40</sup> In what follows, as is customary in control engineering, ~~it is assumed that on the one hand~~ <sup>both</sup> the measured acceleration signal  $b_m$  and ~~on the other~~ the measured substitute acceleration signal  $b_{Em}$ , all losses occurring in the drive in question <sup>are</sup> ~~being~~ disregarded and a mechanically absolutely rigid connection of the surface of the armature rotated engaged by the torque to the position of the rotated part of the rotary acceleration meter at which the effect used for registration of acceleration is generated being taken as a basis, is each scaled so that the relation  $b_m = \alpha \cdot F_g(p) = b_{Em} \cdot F_g(p)$  is satisfied.

④ The measured acceleration signal  $b_m$  is delivered to the input of a low-pass filter 2 (see Figures 1, 2, 3, and 4) with the low-pass transfer function  $FT(p)$ , <sup>with</sup>  $FT(0)$  preferably equaling 1. Hence the signal  $x = b_m \cdot FT(p)$  can be received at the output of the low-pass filter. <sup>2</sup> The measured substitute acceleration signal  $b_{Em}$  is delivered to the input of a high-pass filter 3 (see Figures 1 and

$y = bEm \cdot F_H(p)$

2) with high-pass transfer function  $F_H(p) = FT(0) - FT(p) \cdot$

$F_g(p)$ . Consequently, the signal  $y = bEm \cdot [FT(0) - FT(p) \cdot$

$F_g(p)]$  ~~may be received at this high-pass filter.~~ <sup>is output from the</sup> A signal  $z = bEm$

$FT(p) + bEm [FT(0) - FT(p) \cdot F_g(p)]$  is now formed in accordance with the relation  $z = x + y$ . This synthesized signal is subsequently used as a very high-quality dynamic substitute as the undelayed instantaneous value of the rotary acceleration  $\alpha$  of the rotated armature in automatic control of the drive in ~~as well~~ <sup>as well</sup> question. The difference between the set value ~~as well~~ assigned by a superimposed control system and the synthesized signal  $z$  is delivered to a suitable control unit 4 as control difference (see Figure 1). Delay of the measurement transfer function  $F_g(p)$  and the considerable disturbance of the transfer function  $FM(p)$  are eliminated from the control frequency response, which is of decisive importance for stability, possible limiting cycles, and self-excited oscillations. <sup>4</sup> The last-named transfer function,

$FM(p)$ , describes the mechanical frequency response between the surface of the armature moved which is engaged by the thrust of the drive and the position of the moved part of the accelerometer at which the effect used for registration of acceleration is generated. The low-pass filter with low-pass transfer function  $F_\gamma(p)$  almost entirely eliminates the influence of this mechanical frequency response. So long as transfer function  $FM(p)$  does not deviate significantly from value 1, damping of the low-pass  $F_m(p)$  filter does not exhibit significant values. But, starting with the limit frequency of the low-pass filter, the damping rises sharply, so that the unavoidable resonance step-ups of the mechanical frequency response virtually exert no more influence. <sup>4</sup> The delay of the acceleration signal  $b_m$  by the measurement transfer function  $F_g(p)$  and the delay additionally caused by the low-pass filter are entirely eliminated <sup>the</sup> by signal  $y = bEm \cdot F_H(p)$  at the output of the high-pass filter <sup>3</sup> in the frequency response

$F_g(p)$

in question of the control loop formed by means of the synthesized signal  $z$ .

*system and method of*

*is further described*

The ~~procedure~~ *balance of elements shown* claimed for the invention ~~as presented is also~~ described by the ~~block diagram~~ in Figure 1. The first-order delay element 5 (see Figures, 1, 2, 3, and 4) with amplification  $(VR)$   $V_R$  and time constant  $(T_D)$  describes the delayed reaction of the armature current  $(i_a)$  to change in voltage at the input of the delay element.  $*9$   $T_E$

*4 from  
B000's  
lost  
Fig. 2*

*fA*

*TA*

*In Fig. 2,*  
In a preferred embodiment, the output voltage of the pulse inverter which feeds the armature winding of the drive is derived directly from a two-point control loop ~~14~~, on the principle of the discrete-time switching condition control with a clock frequency  $f_A = 1/T_A$  in the 100-kHz range. Consequently, in Figure 2, the controller 4 is replaced by the two-point element 6, a scanning element 7 with scanning frequency  $f_A = 1/T_A$ , and a zero-order holding element 8. Amplifications  $V$  and  $-V$  in the two-point element 6 take the ratio of converter output voltage to rated voltage of the machine into account. The scanning element 7 and the zero-order holding element 8 allow for the effect of discrete-time switching condition control. In this embodiment of the ~~device claimed for the invention~~ *system and method of*, the limit frequency selected for the low-pass filter 2 with low-pass transfer function  $(F_T(p))$   $F_T(p)$  is to be low enough that no self-excited oscillations occur in the two-point control circuit for synthesized signal  $z$ .

*it occur, as it frequently does,*

Should the ~~circumstance frequently occurring~~ in practical application <sup>s</sup> that the connection between the measured substitute acceleration signal  $b_{Em}$  and the measured acceleration signal  $a_m$  ~~is only incompletely described by the equation~~  $a_m - F_g(p) \cdot b_{Em}$  prove to be a source of disturbance for the quality of the two-

*un*  
*AP 12*  
*10/12*

## system and method

point cascade control, the ~~process claimed for the invention is~~ <sup>may be</sup> expanded. This expansion is characterized by the block diagram ~~shown~~ in Figure 3. In this instance, the transfer function  $FM(p)$  <sup>between</sup>  $F_m(p)$  describes the mechanical frequency response ~~from the surface of the armature set in movement~~ <sup>when it is in motion</sup> (which is engaged by the thrust of the ~~electrical drive~~ <sup>electrical drive</sup> to the position of the part of the accelerometer ~~set in movement at which the effect used for registration of acceleration is generated.~~ <sup>and which is positioned on the surface of the armature and which measures its acceleration.</sup> The relationship between the substitute acceleration signal  $b_{EM}$  and the measured acceleration  $\alpha_m$  is accordingly expressed as  $\alpha_m = FM(p) \cdot F_g(p) \cdot b_{EM}$ . This mechanical frequency response with transfer function  $FM(p)$  (see Figures 3 and 4) is now taken into account in that the high-pass filter 3 with high-pass transfer function  $FH(p) = FT(0) - FT(p) \cdot F_g(p)$  is replaced by a modified high-pass filter 10 with modified high-pass transfer function  $Fh(p) = FT(0) - FT(p) \cdot F_g(p) \cdot FM(p)$ . It is advisable in this process not to ~~determine~~ <sup>set</sup> the limit frequency of the low-pass filter 2 with low-pass transfer function  $FT(p)$  until the high-pass filter 3 with high-pass transfer function  $FH(p)$  has been replaced by modified high-pass filter 10 with modified high-pass transfer function  $Fh(p)$ .

Should the transfer function  $FM(p)$  have a plurality of polar and/or zero positions, development of the high-pass filter 10 with modified high-pass transfer function  $Fh(p)$  is found to be very costly. In order to reduce this cost in development of this high-pass filter 10, the ~~process claimed for the invention may be~~ <sup>system and method of</sup> further modified as described in the following. <sup>A part</sup>

shown in Fig. 4.

$$F_0(p) = \frac{(1+p \cdot T_{v1}) \cdot (1+2 \cdot D_{v1} \cdot p \cdot T_{v1} + p^2 \cdot T_{v1}^2) \cdot \dots}{(1+p \cdot T_{f1}) \cdot (1+2 \cdot D_{f1} \cdot p \cdot T_{f1} + p^2 \cdot T_{f1}^2) \cdot \dots}$$

\*  $10^{-4}$  (new 4)

~~is separated from the transfer function of the mechanical frequency response.~~ This part allows for one or more poles



\*104 Fig 4 illustrates a control system

for a plurality of electric drive types

in accordance with <sup>alternative</sup> a third embodiment

of the invention. In Fig. 4, the transfer  
function  $F_m(p)$  of Fig. 3 has been

separated into two components,  $F_{m,rest}(p)$

and  $F_o(p)$ .  $F_o(p)$  is defined as follows:

and/or zero positions with particularly high values of  $T\mu$ ,  $Tv$ ,  $Ti$ , or  $Tj$ . The transfer function of the mechanical frequency response may be described as follows

$$F_M(p) = F_0(p) \cdot F_{M,Rest}(p) \quad \text{with} \quad F_{M,Rest}(p) = F_M(p) \cdot F_0^{-1}(p).$$

The mechanical frequency response with transfer function  $F_M(p)$  9 is now taken into account only in approximation ~~by the in~~ ~~circumstance~~ that the high-pass filter 3, with high-pass transfer function  $F_H(p) = F_T(0) - F_T(p) \cdot F_g(p)$  is replaced by a modified high-pass filter 11 with modified high-pass transfer function  $F_{h^*}(p) \approx F_T(0) - F_T(p) \cdot F_g(p) \cdot F_0(p)$ . It is advisable not to determine the limit frequency of the low-pass filter 2 with low-pass transfer function  $F_T(p)$  in this process until the high-pass filter 3 with high-pass transfer function  $F_H(p)$  has been replaced by modified high-pass filter 11 with modified high-pass transfer function  $F_{h^*}(p)$ . ~~The proposed process claimed for the invention is described by the block diagram in Figure 4.~~

\*"attached.

Abstract

Add attached.

\*"

The present invention has been described w/reference to certain exemplary embodiments thereof. However, it will be readily apparent to those skilled in the art that it is possible to embody the invention in specific forms other than those of the exemplary embodiments described above. This may be done without departing from the spirit and scope of the invention. The exemplary embodiments are merely illustrative and should not be considered restrictive in any way. The scope of the invention ~~is~~ is defined by the appended claims and their equivalents, rather than the preceding description. -

[A system and method for the generation of a partly synthesized high-quality signal for acceleration of an armature of an electric drive]

ABSTRACT

A system and method for controlling the acceleration of an armature of an electric drive by generating a high quality acceleration error correction signal  $z$ , the system comprising an accelerometer for obtaining a measured armature acceleration value  $\underline{b}_m$ , which is equal to the product of a true armature acceleration  $\alpha$ , and an acceleration measurement transfer function  $F_g(p)$ , and means for obtaining a measured acceleration signal,  $\underline{b}_{Em}$ , which is generated from a measured substitute acceleration signal  $\underline{b}_E$ .  $\underline{b}_m$  and  $\underline{b}_{Em}$  are scaled such that the relationship of  $\underline{b}_m = \alpha \cdot F_g(p) = \underline{b}_{Em} \cdot F_g(p)$  is satisfied. The measured armature acceleration signal  $\underline{b}_m$  is filtered with a first filter transfer function of  $F_T(p)$ , and the measured acceleration signal  $\underline{b}_{Em}$  is filtered with a second filter transfer function of  $F_H(p)$ . The first and second filter outputs are combined to form the partly synthesized high quality acceleration error correction signal  $z = \underline{b}_m \cdot F_T(p) + \underline{b}_{Em} \cdot F_H(p)$ .